

Amendments to the Claims:

This listing of claims will replace all prior versions, and listings, of claims in the application:

Listing of Claims:

1. (Currently amended) ~~A portable instrument~~ Portable apparatus for measuring parameters of optical signals propagating concurrently in opposite directions in an optical transmission path (16, 16/1,..., 16/9) between two elements (10, 14/1...14/9), at least one (14/1...14/9) of the elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2) from the other (10) of said elements, the instrument ~~being characterized by comprising~~ first and second connector means (22, 24) for connecting the instrument into the optical transmission path in series therewith, and means (32, 38, 46) connected between the first and second connector means for propagating at least said second optical signal (S2) towards said at least one (14) of the elements, and measuring said parameters of said concurrently propagating optical signals (S1, S2).

2. (Currently amended) ~~A portable instrument~~ Apparatus according to claim 1, characterized in that wherein the propagating and measuring means (32, 38, 46) provides an optical signal path between the first and second connector means (22, 24) for conveying at least a portion of said second optical signal (S2).

3. (Currently amended) ~~A portable instrument~~ Apparatus according to claim 2, characterized in that wherein the propagating and measuring means (32, 38, 46) comprises:

coupler means (32) having first and second ports (28, 30) connected to the first and second connector means (22, 24), respectively, to provide said optical signal path to convey said first (S1) and second (S2) optical signals in opposite directions between said first and second connector means (22, 24), and a third port (34) for supplying a portion (S1') of said first optical signal (S1),

detection means (38; 38, 42; 38, 42, 44) for converting at least the first optical signal portion (S1') into a corresponding electrical signal, and

measuring means (46) for processing the electrical signal to provide an indication of said measured parameters.

4. (Currently amended) ~~An instrument~~ Apparatus according to claim 3, characterized in that wherein the coupler means (32) has a fourth port (36) for supplying a portion (S2') of said second optical signal (S2), the detection means (38; 38, 42; 38, 42, 44) also converting at least part of the

second optical signal portion (S2') into a corresponding second electrical signal, and the measuring means (46) processing both of the electrical signals to provide desired measurement values of parameters for each of the counter-propagating signals.

5. (Currently amended) ~~An instrument Apparatus~~ according to claim 1, ~~2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 30, 31, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 62, 63, 64, 65, 66, 67, 68, 69, 70, 71, 72, 73, 74, 75, 76, 77, 78, 79, 80, 81, 82, 83, 84, 85, 86, 87, 88, 89, 90, 91, 92, 93, 94, 95, 96, 97, 98, 99, 100, 101, 102, 103, 104, 105, 106, 107, 108, 109, 110, 111, 112, 113, 114, 115, 116, 117, 118, 119, 120, 121, 122, 123, 124, 125, 126, 127, 128, 129, 130, 131, 132, 133, 134, 135, 136, 137, 138, 139, 140, 141, 142, 143, 144, 145, 146, 147, 148, 149, 150, 151, 152, 153, 154, 155, 156, 157, 158, 159, 160, 161, 162, 163, 164, 165, 166, 167, 168, 169, 170, 171, 172, 173, 174, 175, 176, 177, 178, 179, 180, 181, 182, 183, 184, 185, 186, 187, 188, 189, 190, 191, 192, 193, 194, 195, 196, 197, 198, 199, 200, 201, 202, 203, 204, 205, 206, 207, 208, 209, 210, 211, 212, 213, 214, 215, 216, 217, 218, 219, 220, 221, 222, 223, 224, 225, 226, 227, 228, 229, 230, 231, 232, 233, 234, 235, 236, 237, 238, 239, 240, 241, 242, 243, 244, 245, 246, 247, 248, 249, 250, 251, 252, 253, 254, 255, 256, 257, 258, 259, 260, 261, 262, 263, 264, 265, 266, 267, 268, 269, 270, 271, 272, 273, 274, 275, 276, 277, 278, 279, 280, 281, 282, 283, 284, 285, 286, 287, 288, 289, 290, 291, 292, 293, 294, 295, 296, 297, 298, 299, 300, 301, 302, 303, 304, 305, 306, 307, 308, 309, 310, 311, 312, 313, 314, 315, 316, 317, 318, 319, 320, 321, 322, 323, 324, 325, 326, 327, 328, 329, 330, 331, 332, 333, 334, 335, 336, 337, 338, 339, 340, 341, 342, 343, 344, 345, 346, 347, 348, 349, 350, 351, 352, 353, 354, 355, 356, 357, 358, 359, 360, 361, 362, 363, 364, 365, 366, 367, 368, 369, 370, 371, 372, 373, 374, 375, 376, 377, 378, 379, 380, 381, 382, 383, 384, 385, 386, 387, 388, 389, 390, 391, 392, 393, 394, 395, 396, 397, 398, 399, 400, 401, 402, 403, 404, 405, 406, 407, 408, 409, 410, 411, 412, 413, 414, 415, 416, 417, 418, 419, 420, 421, 422, 423, 424, 425, 426, 427, 428, 429, 430, 431, 432, 433, 434, 435, 436, 437, 438, 439, 440, 441, 442, 443, 444, 445, 446, 447, 448, 449, 450, 451, 452, 453, 454, 455, 456, 457, 458, 459, 460, 461, 462, 463, 464, 465, 466, 467, 468, 469, 470, 471, 472, 473, 474, 475, 476, 477, 478, 479, 480, 481, 482, 483, 484, 485, 486, 487, 488, 489, 490, 491, 492, 493, 494, 495, 496, 497, 498, 499, 500, 501, 502, 503, 504, 505, 506, 507, 508, 509, 510, 511, 512, 513, 514, 515, 516, 517, 518, 519, 520, 521, 522, 523, 524, 525, 526, 527, 528, 529, 530, 531, 532, 533, 534, 535, 536, 537, 538, 539, 540, 541, 542, 543, 544, 545, 546, 547, 548, 549, 550, 551, 552, 553, 554, 555, 556, 557, 558, 559, 560, 561, 562, 563, 564, 565, 566, 567, 568, 569, 570, 571, 572, 573, 574, 575, 576, 577, 578, 579, 580, 581, 582, 583, 584, 585, 586, 587, 588, 589, 590, 591, 592, 593, 594, 595, 596, 597, 598, 599, 600, 601, 602, 603, 604, 605, 606, 607, 608, 609, 610, 611, 612, 613, 614, 615, 616, 617, 618, 619, 620, 621, 622, 623, 624, 625, 626, 627, 628, 629, 630, 631, 632, 633, 634, 635, 636, 637, 638, 639, 640, 641, 642, 643, 644, 645, 646, 647, 648, 649, 650, 651, 652, 653, 654, 655, 656, 657, 658, 659, 660, 661, 662, 663, 664, 665, 666, 667, 668, 669, 670, 671, 672, 673, 674, 675, 676, 677, 678, 679, 680, 681, 682, 683, 684, 685, 686, 687, 688, 689, 690, 691, 692, 693, 694, 695, 696, 697, 698, 699, 700, 701, 702, 703, 704, 705, 706, 707, 708, 709, 710, 711, 712, 713, 714, 715, 716, 717, 718, 719, 720, 721, 722, 723, 724, 725, 726, 727, 728, 729, 730, 731, 732, 733, 734, 735, 736, 737, 738, 739, 740, 741, 742, 743, 744, 745, 746, 747, 748, 749, 750, 751, 752, 753, 754, 755, 756, 757, 758, 759, 760, 761, 762, 763, 764, 765, 766, 767, 768, 769, 770, 771, 772, 773, 774, 775, 776, 777, 778, 779, 780, 781, 782, 783, 784, 785, 786, 787, 788, 789, 790, 791, 792, 793, 794, 795, 796, 797, 798, 799, 800, 801, 802, 803, 804, 805, 806, 807, 808, 809, 810, 811, 812, 813, 814, 815, 816, 817, 818, 819, 820, 821, 822, 823, 824, 825, 826, 827, 828, 829, 830, 831, 832, 833, 834, 835, 836, 837, 838, 839, 840, 841, 842, 843, 844, 845, 846, 847, 848, 849, 850, 851, 852, 853, 854, 855, 856, 857, 858, 859, 860, 861, 862, 863, 864, 865, 866, 867, 868, 869, 870, 871, 872, 873, 874, 875, 876, 877, 878, 879, 880, 881, 882, 883, 884, 885, 886, 887, 888, 889, 890, 891, 892, 893, 894, 895, 896, 897, 898, 899, 900, 901, 902, 903, 904, 905, 906, 907, 908, 909, 910, 911, 912, 913, 914, 915, 916, 917, 918, 919, 920, 921, 922, 923, 924, 925, 926, 927, 928, 929, 930, 931, 932, 933, 934, 935, 936, 937, 938, 939, 940, 941, 942, 943, 944, 945, 946, 947, 948, 949, 950, 951, 952, 953, 954, 955, 956, 957, 958, 959, 960, 961, 962, 963, 964, 965, 966, 967, 968, 969, 970, 971, 972, 973, 974, 975, 976, 977, 978, 979, 980, 981, 982, 983, 984, 985, 986, 987, 988, 989, 990, 991, 992, 993, 994, 995, 996, 997, 998, 999, 1000~~, characterized ~~in that wherein~~, where said one of the elements (14/1,..., 14/9) also receives via said optical transmission path a third optical signal (S3) at a different wavelength from that of said second optical signal (S2), the propagating and measuring means (46) further comprises means (40, 44, 52, 58; 44, 58, 68) for measuring parameters of the third optical signal (S3).

6. (Currently amended) ~~An instrument Apparatus~~ according to claim 4, ~~characterized in that wherein~~, where said one of the elements (14/1,..., 14/9) also normally receives via the optical transmission path a third optical signal (S3) at a different wavelength to that of said second optical signal (S2), the propagating and measuring means (46) further comprises a splitter (40) connected to the coupler means (32) for splitting a corresponding optical signal portion (S2', S3') into two parts (S2'', S3''), each comprising portions of both the second and third optical signals, and filter means (64, 66) coupled to the splitter (40) for separating the two parts according to wavelength before supplying same to said detection means (38, 42, 44).

7. (Currently amended) ~~An instrument Apparatus~~ according to claim 4, ~~characterized in that wherein~~, where said one of the elements (14/1,..., 14/9) also normally receives via the optical transmission path a third optical signal (S3) at a wavelength different from that of said second optical signal (S2), said propagating and measuring means comprises a wavelength discriminator (68) connected to the coupler (32) for separating at least a portion (S2', S3') of the combined second and third optical signals (S2, S3) according to wavelength before to obtain corresponding separate portions (S2'', S3'') and supplying same to said detection means (38, 42, 44).

8. (Currently amended) ~~An instrument Apparatus~~ according to ~~any of claims 1 to 7~~, ~~characterized in that claim 1, wherein~~ the measuring means comprises a separate detector (38, 42, 44) for each of the measured optical ~~signals~~ signal portions.

9. (Currently amended) ~~An instrument Apparatus~~ according to ~~any one of claims 1 to 8~~, ~~characterized in that claim 1, wherein~~, where one of the optical signals is analog, the measuring means (46) is arranged to extract the time-averaged optical power of the signal.

10. (Currently amended) ~~An instrument Apparatus according to any one of claims 1 to 8, characterized in that~~ claim 1, wherein, where one (S1) of the optical signals comprises bursts of digital data alternating with lulls, the measuring means (46) is arranged to extract the average of the optical power averaged over the duration of the individual bursts.

11. (Currently amended) ~~An instrument Apparatus according to any one of claims 1 to 10, characterized in that~~ claim 1, wherein the measuring means (46) comprises custom circuitry.

12. (Currently amended) ~~An instrument Apparatus according to any of claims 1 to 10, characterized in that~~ claim 1, wherein the measuring means (46) comprises a suitably-programmed microcomputer.

13. (Currently amended) ~~An instrument Apparatus according to any one of claims 1 to 12, characterized in that~~ claim 1, wherein said measuring means further comprises display means (60) for displaying the parameter measurements.

14. (Currently amended) A method of measuring parameters of at least one of optical signals propagating concurrently in opposite directions in an optical transmission path (16, 16/1,..., 19/9) between two elements (10, 14/1...14/9), at least one (14/1...14/9) of the elements being operative to transmit a first optical signal (S1) only if it continues to receive a second optical signal (S2), the method being ~~characterized by comprising~~ the steps of:

connecting first and second connector means (22, 24) of an instrument into the optical transmission path in series therewith,

using the instrument to propagate at least said second optical signal (S2) towards said at least one (14) of the elements, and

measuring said parameters of said concurrently propagating optical signals.

15. (Currently amended) A method according to claim 14, ~~characterized in that wherein~~ the instrument provides an optical signal path between the first and second connector means (22, 24) for at least said second optical signal (S2).

16. (Currently amended) A method according to claim 15, ~~characterized in that wherein~~ the instrument has a coupler means (32) having first and second ports (28,30) connected to the first and second connector means (22, 24), respectively, to provide said optical signal path for conveying said first (S1) and second (S2) optical signals in opposite directions between said first and second connector means (22, 24), and a third port (34) for a portion (S1') of said first optical signal (S1) propagating in said optical signal path, the method comprising the steps of:

extracting said portion (S1') of said first optical signal (S1) from said third port of the coupler means,

converting the first optical signal portion (S1') into a corresponding first electrical signal, and processing the first electrical signal to provide an indication of said measured parameters.

17. (Currently amended) A method according to claim 16, characterized by further comprising the steps of

extracting from a fourth port (36) of the coupler (32) a portion (S2') of said second optical signal (S2) propagating in the optical signal path;

converting the second optical signal portion (S2') into a corresponding second electrical signal; and

processing said first and second electrical signals to provide the desired parameters for each of the counter-propagating optical signals.

18. (Currently amended) A method according to claim 14, ~~15, 16 or 17~~, characterized in that wherein, where said one of the elements (14/1,..., 14/9) also receives via the optical transmission path a third optical signal (S3) at a wavelength different from that of said second optical signal (S2), the measuring step also measures parameters of the third optical signal (S3).

19. (Currently amended) A method according to claim 17, ~~characterized in that wherein~~, where said one of the elements (14/1,..., 14/9) also receives via the optical transmission path a third optical signal (S3) co-propagating with the said second optical signal (S2) at a wavelength different from that of the said second optical signal (S2), the measuring step includes the steps of splitting a portion of the co-propagating optical signals into two parts, each comprising portions of the second and third optical signals (S2, S3), separating each of the two parts according to wavelength, converting said parts into said second electrical signal and a third electrical signal, respectively, and also processing the third electrical signal to obtain parameters of the third optical signal (S3).

20. (Currently amended) A method according to claim 17, ~~characterized in that wherein~~, where said one of the elements (14/1,..., 14/9) also receives via the optical transmission path a third optical signal (S3) co-propagating with the said second optical signal (S2) at a wavelength different from that of the said second optical signal (S2), said measuring step employs a wavelength discriminator (68) connected to the coupler (32) for splitting a portion of the co-propagating optical signals into two parts each corresponding to a respective one of the second and third optical signals, , converting the parts to said second electrical signal and a third electrical signal, and also processing the third electrical signal to obtain parameters of said third optical signal (S3).

21. (Currently amended) A method according to ~~any one of claims 14 to 20, characterized in that claim 14, wherein~~ the detection step uses a separate detector (38, 42, 44) for each of the measured optical signals.

22. (Currently amended) A method according to ~~any one of claims 14 to 21, characterized in that claim 14, wherein~~, where one of the optical signals is analog, the detection and processing derives the time-averaged optical power of the signal.

23. (Currently amended) A method according to ~~any one of claims 14 to 21, characterized in that claim 14, wherein~~, where one (S1) of the optical signals comprises bursts of digital data alternating with lulls, the detection and processing derives the average of the optical power averaged over the duration of the individual bursts.

24. (Currently amended) A method according to ~~any one of claims 14 to 23, characterized in that claim 14, wherein~~ the processing is performed using custom circuitry.

25. (Currently amended) A method according to ~~any of claims 14 to 23, characterized in that claim 14, wherein~~ the processing is performed using a suitably-programmed microcomputer.

26. (Currently amended) A method according to ~~any one of claims 14 to 25, further characterized by claim 14, further comprising~~ the step of displaying the parameter measurements.

27. (Currently amended) A method according to ~~any one of claims 14 to 26, characterized in that claim 14, wherein~~ the measurements are performed upon optical signals propagating concurrently in opposite directions in an optical transmission path between network elements in a passive optical network.